## **Table of Contents**

DDAS tracing	-
DRAS CLACILLY	 _

## **BRAS** tracing

[Stingray Service Gateway 7.5] L2 BRAS implementing is often challenging, since it requires not only the SSG BRAS, but also the environment. Also SSG operating in the L2 BRAS mode modifies packets, drops some of them, so there are situations in which you need to know how the L2 BRAS operates at the packet level.

The following fastdpi.conf options designed to do this:

bras trace - BRAS tracing. Tracing modes bitmask:

- 0x0001 ARP request tracing (bras\_arp\_proxy mode has to be enabled)
- 0x0002 IP source guard tracing (bras ip source guard mode has to be enabled)
- 0x0004 tracing of the local traffic termination (bras\_terminate\_local mode has to be enabled)
- 0x0008 tracing of the VLAN traffic termination/origination (bras\_vlan\_terminate mode has to be enabled)
- 0x0010 tracing of the DHCP callback within slave flow
- 0x0020 PPPoE packets tracing
- 0x0040 PPP FSA transition tracing
- 0x0080 to capture PPPoE packets using pcap; if the bras\_pppoe\_trace\_mac option is not specified all the PPPoE traffic is written
- 0x0100 ICMP echo tracing
- 0x20000 LAG tracing



Note that the tracing modes are **highly** resource-consuming since the BRAS operating in such modes actively writes to the fastdpi\_slave\_x.log files. It is not recommended to apply tracing modes to the SSG at peak times.

bras\_save\_drop - if this parameter equals to 1 then the SSG writes to pcap all the packets including those it has decided to drop (do not forward to any destination). For the dropped IP packets ttl = 0, so the IP header checksum is recalculated. If the ajb\_save\_ip parameter is specified, only packets for this address are recorded. If ajb\_save\_ip is not specified, all dropped packets are recorded.

bras\_save\_term - a value of 1 means that the SSG records all the output packets in pcap after the termination. This option works only in conjunction with the ajb\_save\_ip option: the output packets would be written to pcap only for the IP addresses (or CIDR) specified within this option. Thus after the termination, you would see two packages in pcap - the input and output ones.

bras\_pppoe\_trace\_mac [the SSG 8.1] - the option specifies the MAC address of the PPPoE subscriber whose packets should be stored in pcap. This parameter is valid only with the 0x0080 flag within the bras\_trace option, i.e. to capture the PPPoE subscriber packets you should specify the 0x0080 flag within the bras\_trace option and set the subscriber MAC address using the 'xx:xx:xx:xx:xx:xx' format, for example:

bras\_trace=0x0080
bras\_pppoe\_trace\_mac=20:28:18:a0:a9:b6