Содержание

Classifier configuration

To open the "Classifier configuration" section, open the main menu, point to the "Classifier" item and click on the "Configuration" item. (fig. 1)

A	CKAT DPI : Fast	DPI	~ 0					
	УПРАВЛЕНИЕ DPI	,	СИФИКАТОР / МОДЕЛЬ КЛАССИФИКАТ					
🚓 Катег	УПРАВЛЕНИЕ УСЛУГАМИ	•						
🔘 Моде	QOE АНАЛИТИКА	•	Папки	<				
🗐 Конф	CEPBIICH VAS CLOUD			e				
	На классификатор	•	🚓 КАТЕГОРИИ САЙТОВ					
S JION	2 АДМИНИСТРАТОР	•	О МОДЕЛЬ КЛАССИФИКАТОРА) ~				
	>_ SSH ТЕРМИНАЛ УСТРОЙСТВА		КОНФИГУРАЦИЯ					
			<i>а</i> логи	0				

<html><center></html> (fig. 1) <html></center></html>

The section looks like the picture below. (fig. 2)

E Cosperato 13								
E Cosperanto 15								
	E Cospensito. 15			Copera Copera			(b) Pearing	
GE Hactpoline	Prompy dd							
Pecampa-clickatean	•							
Fegerse-even x 8/1 MySrd	① Ten sope	a 0 ner 0	Raj () Butterraria	O Potaque n	Ф. Зарерика в	() Passeg	() No.00	@ Skinger
Hactpolioi sogene	22 v/p	19012		10		10	0	
	Роскворь сКоллали Гладорочника к. М.(1. Мубя) Настранов кодели	Focuseur didatment + Transvorvene Hall Mybrid ID Hacrypolice wagehov ID	Piccespic district * Prannowski fd2.0/hdg @ fbai kagas @ mayst @ Hacrypolitie segarie 20 v/p 00/12 #	Focuse: Statust * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * * <	Focusion: distances Procession: editability Improvement editab	Picanpe domain + Transcover (%21%)%/ © %as aspts © flags © %as, or %aspts © %aspts	Piccespic clistratin * Transcense (h210/h5f) © © Teal stages © Piccespic Stage © Notaget A © Teal piccespic © Piccespic Display Display <thdisplay< th=""> Display Disp</thdisplay<>	Piconspic distribution Piconspiconspic distribution Piconspic distrib

<html><center></html> (fig. 2) <html></center></html>

"Classifier configuration" has sections:

- 1. Settings:
 - 1. Button "Save" saves changes in the configuration of the classifier.
 - 2. "Restart" button restarts the classifier with the updated configuration.
 - 3. "Refresh" button requests the last saved configuration from the server.
 - 4. Switch "Form / Editor" toggles the editing modes of the configurator
 - 1. Form allows you to edit the server configuration using the graphical interface.
 - 2. Editor allows you to edit the server configuration by editing the configuration file directly, that is, in text format.
- 2. List of configuration categories:
 - 1. Clickstream receivers

- 1. Button "+" opens a form (fig. 3) for adding a receiver.
- 2. List of receivers.
- 3. Connection to MySql DB
 - 1. DB connection type (DB_CONNECTION)
 - 2. Database host (DB_HOST)
 - 3. DB port (DB_PORT)
 - 4. Database name (DB_DATABASE)
 - 5. Database username (DB_USERNAME)
 - 6. DB password (DB_PASSWORD)
- 4. Model settings
 - 1. Default models (CFG_SITES_CLSFR_MODEL)



<html><center></html> (fig. 3) <html></center></html>