

# **Содержание**

<b>PCAP Record Management and VLAN Mirroring .....</b>	<b>3</b>
<i>PCAP record management .....</i>	<i>3</i>
<i>Mirroring on a VLAN .....</i>	<i>4</i>



# PCAP Record Management and VLAN Mirroring

## PCAP record management

12 service includes PCAP recording for all subscriber traffic. The PCAP file is placed in the path specified in the basic configuration in fastdpi.conf:

```
ajb_udpi_path
```

One can control start and stop of the recording on the platform by SM fdpi\_ctrl utility when the parameter ajb\_reserved=1 is set:

```
fdpi_ctrl setenv --ajb_save_url 1  
fdpi_ctrl setenv --ajb_save_udpi 1
```

Enabling PCAP recording:

```
fdpi_ctrl load --service 12 --ip 192.168.1.1  
fdpi_ctrl load --service 12 --login USER101
```

Disabling PCAP recording:

```
fdpi_ctrl del --service 12 --ip 192.168.1.1  
fdpi_ctrl del --service 12 --login USER101
```

To quickly find data in a PCAP file, you can create a file with indexed data by turning on the settings in /etc/dpi/fastdpi.conf:

```
ajb_pcap_ind_mask=1
```

Here:

- 0 - index is not created (default value)
- 1 - IPv4
- 2 - IPv6
- 3 - both IPv4 and IPv6.



If other recording methods are enabled for this subscriber (ajb\_save\_udpi or ajb\_save\_ip), then SESSION\_ID will be not recorded to the resulting index.

## Mirroring on a VLAN

17 service includes mirroring of subscriber traffic to a specific VLAN that is swept into the data ports of the SCAT. the traffic direction is preserved.

Setup in fastdpi.conf:

```
span_vlan=123  
span_trace=1
```

You can use one of the parameters in fastdpi.conf for diagnostics:

```
trace_ip  
span_trace  
ajb_save_emit
```



If we set service 12 and 17, we will see the original recording and the mirrored recording in PCAP.