

Содержание

S6b Authorization Interface Settings	3
<i>Section "fast-epdg.auth.s6b"</i>	3
<i>Section "fast-epdg.auth.s6b.<diameter-s6b-client-name-n>"</i>	3

S6b Authorization Interface Settings

Section "fast-epdg.auth.s6b"

Parameter	Description	Value
realm	Serviced realm	epc.mncYYY.mccXXX.3gppnetwork.org
host	Server hostname	epdg.epc.mncYYY.mccXXX.3gppnetwork.org
<diameter-s6b-client-name-1> {}	S6b Server #1 parameters	
<diameter-s6b-client-name-2> {}	S6b Server #2 parameters	
<diameter-s6b-client-name-n> {}	S6b Server #n parameters	

Template:

```
fast-epdg {  
  auth {  
    interface =  
    s6b {  
      realm =  
      host =  
      <server-name> {}  
    }  
  }  
}
```

Example:

```
fast-epdg {  
  auth {  
    interface = SWx  
    s6b {  
      realm = epc.mnc002.mcc250.3gppnetwork.org  
      host = epdg.epc.mnc002.mcc250.3gppnetwork.org  
      <server-name> {}  
    }  
  }  
}
```

Section "fast-epdg.auth.s6b.<diameter-s6b-client-name-n>"

Parameter	Description	Value
local	Client address:port	AAA.BBB.CCC.DDD:XXXX, [1111.2222.3333.4444.5555.6666.7777.8888]:XXXX

Parameter	Description	Value
remote	Server address:port	AAA.BBB.CCC.DDD:XXXX, [1111.2222.3333.4444.5555.6666.7777.8888]:XXXX
proto	Transport protocol	[sctp][tcp]

Template:

```
fast-epdg {
  auth {
    interface =
    s6b {
      realm =
      host =
      diameter-s6b-client-1 {
        priority =
        local =
        remote =
        proto =
      }
      diameter-s6b-client-2 {
        priority =
        local =
        remote =
        proto =
      }
      diameter-s6b-client-3 {
        priority =
        local =
        remote =
        proto =
      }
    }
  }
}
```

Example:

```
fast-epdg {
  auth {
    interface = SWx
    s6b {
      realm = epc.mnc002.mcc250.3gppnetwork.org
      host = epdg.epc.mnc002.mcc250.3gppnetwork.org
      diameter-s6b-client-1 {
        priority =
        local = 192.168.1.1:3868
        remote = 192.168.2.1:3868
        proto = sctp
      }
      diameter-s6b-client-2 {
        priority =
```

```
    local = 192.168.1.1:3869
    remote = 192.168.2.2:3868
    proto = sctp
}
diameter-s6b-client-3 {
    priority =
    local = 192.168.1.1:3870
    remote = 192.168.2.3:3868
    proto = tcp
}
}
}
```