

Содержание

S6b Authorization Interface Settings	3
<i>Section "fast-epdg.auth"</i>	3
<i>Section "fast-epdg.auth.s6b"</i>	3
<i>Section "fast-epdg.auth.s6b.<diameter-s6b-client-name-n>"</i>	4

S6b Authorization Interface Settings

Section "fast-epdg.auth"

Parameter	Description	Value
iface	Used interface	[SWm][SWx]

Template:

```
fast-epdg {
  auth {
    iface =
    swm {}
    swx {}
    s6b {}
  }
}
```

Section "fast-epdg.auth.s6b"

Parameter	Description	Value
realm	Serviced realm	epc.mncYYY.mccXXX.3gppnetwork.org
host	Server hostname	epdg.epc.mncYYY.mccXXX.3gppnetwork.org
<diameter-s6b-client-name-1> {}	S6b Server #1 parameters	
<diameter-s6b-client-name-2> {}	S6b Server #2 parameters	
<diameter-s6b-client-name-n> {}	S6b Server #n parameters	

Template:

```
fast-epdg {
  auth {
    iface =
    s6b {
      realm =
      host =
      <server-name> {}
    }
  }
}
```

Example:

```
fast-epdg {
```

```

auth {
  iface = SWx
  s6b {
    realm = epc.mnc002.mcc250.3gppnetwork.org
    host = epdg.epc.mnc002.mcc250.3gppnetwork.org
    <server-name> {}
  }
}

```

Section "fast-epdg.auth.s6b.<diameter-s6b-client-name-n>"

Parameter	Description	Value
local	Client address:port	AAA.BBB.CCC.DDD:XXXX, [1111.2222.3333.4444.5555.6666.7777.8888]:XXXX
remote	Server address:port	AAA.BBB.CCC.DDD:XXXX, [1111.2222.3333.4444.5555.6666.7777.8888]:XXXX
proto	Transport protocol	[sctp][tcp]

Template:

```

fast-epdg {
  auth {
    iface =
    s6b {
      realm =
      host =
      diameter-s6b-client-1 {
        priority =
        local =
        remote =
        proto =
      }
      diameter-s6b-client-2 {
        priority =
        local =
        remote =
        proto =
      }
      diameter-s6b-client-3 {
        priority =
        local =
        remote =
        proto =
      }
    }
  }
}

```

Example:

```
fast-epdg {
  auth {
    iface = SWx
    s6b {
      realm = epc.mnc002.mcc250.3gppnetwork.org
      host = epdg.epc.mnc002.mcc250.3gppnetwork.org
      diameter-s6b-client-1 {
        priority =
        local = 192.168.1.1:3868
        remote = 192.168.2.1:3868
        proto = sctp
      }
      diameter-s6b-client-2 {
        priority =
        local = 192.168.1.1:3869
        remote = 192.168.2.2:3868
        proto = sctp
      }
      diameter-s6b-client-3 {
        priority =
        local = 192.168.1.1:3870
        remote = 192.168.2.3:3868
        proto = tcp
      }
    }
  }
}
```