

Содержание

SWa Authorization Interface Settings	3
Section "charon.plugins.eap-diameter.swa"	3
Section "charon.plugins.eap-diameter.swa.<diameter-aaa-client-name-n>"	3

SWa Authorization Interface Settings

Section "charon.plugins.eap-diameter.swa"

Parameter	Description	Value
app_id	Application ID	swa
realm	Serviced realm	epc.mncYYY.mccXXX.3gppnetwork.org
host	Client hostname	epdg.epc.mncYYY.mccXXX.3gppnetwork.org
vendor_id	Vendor ID	[none][3gpp]
<diameter-aaa-client-name-1> {}	AAA Client #1 parameters	
<diameter-aaa-client-name-2> {}	AAA Client #2 parameters	
<diameter-aaa-client-name-n> {}	AAA Client #n parameters	

Example:

```
charon {
    plugins {
        eap-diameter {
            interface = SWm
            swa {
                app_id = swa
                realm =
epc.mnc002.mcc250.3gppnetwork.org
                host =
epdg.epc.mnc002.mcc250.3gppnetwork.org
                vendor_id = 3gpp
                diameter-aaa-client-name-1 {}
                diameter-aaa-client-name-2 {}
                diameter-aaa-client-name-n {}
            }
        }
    }
}
```

Section "charon.plugins.eap-diameter.swa.<diameter-aaa-client-name-n>"

Parameter	Description	Value
local	AAA Server address:port	AAA.BBB.CCC.DDD:XXXX, [1111.2222.3333.4444.5555.6666.7777.8888]:XXXX
remote	AAA Client address:port	AAA.BBB.CCC.DDD:XXXX, [1111.2222.3333.4444.5555.6666.7777.8888]:XXXX

Parameter	Description	Value
proto	Transport protocol	[sctp][tcp]

Example:

```

charon {
    plugins {
        eap-diameter {
            interface = SWm
            swa {
                app_id = swa
                realm =
epc.mnc002.mcc250.3gppnetwork.org
                host =
epdg.epc.mnc002.mcc250.3gppnetwork.org
                vendor_id = 3gpp
                diameter-aaa-client-1 {
                    local =
192.168.1.1:3868
                    remote =
192.168.2.1:3868
                    proto = sctp
                }
                diameter-aaa-client-2 {
                    local =
192.168.1.1:3869
                    remote =
192.168.2.2:3868
                    proto = tcp
                }
            }
        }
    }
}

```