

Содержание

SWm Authorization Interface Settings	3
Section "fast-epdg.auth.swm"	3
Section "fast-epdg.auth.swm.<diameter-aaa-server-name-n>"	3

SWm Authorization Interface Settings

Section "fast-epdg.auth.swm"

Parameter	Description	Value
realm	Serviced realm	epc.mncYYY.mccXXX.3gppnetwork.org
host	Client hostname	epdg.epc.mncYYY.mccXXX.3gppnetwork.org
<diameter-aaa-server-name-1> {}	AAA Server #1 parameters	
<diameter-aaa-server-name-2> {}	AAA Server #2 parameters	
<diameter-aaa-server-name-n> {}	AAA Server #n parameters	

Template:

```
fast-epdg {
    auth {
        interface =
        swm {
            realm =
            host =
            <server-name> {}
        }
    }
}
```

Example:

```
fast-epdg {
    auth {
        interface = SWm
        swm {
            realm = epc.mnc002.mcc250.3gppnetwork.org
            host = epdg.epc.mnc002.mcc250.3gppnetwork.org
            <server-name> {}
        }
    }
}
```

Section "fast-epdg.auth.swm.<diameter-aaa-server-name-n>"

Parameter	Description	Value
priority	Balancing priority	0-100

Parameter	Description	Value
local	Client address:port	AAA.BBB.CCC.DDD:XXXX, [1111.2222.3333.4444.5555.6666.7777.8888]:XXXX
remote	AAA server address:port	AAA.BBB.CCC.DDD:XXXX, [1111.2222.3333.4444.5555.6666.7777.8888]:XXXX
proto	Transport protocol	[sctp][tcp]

Template:

```
fast-epdg {
    auth {
        interface =
        swm {
            realm =
            host =
            diameter-aaa-server-1 {
                priority =
                local =
                remote =
                proto =
            }
            diameter-aaa-server-2 {
                priority =
                local =
                remote =
                proto =
            }
        }
    }
}
```

Example:

```
fast-epdg {
    auth {
        interface = SWm
        swm {
            realm = epc.mnc002.mcc250.3gppnetwork.org
            host = epdg.epc.mnc002.mcc250.3gppnetwork.org
            diameter-aaa-server-1 {
                priority = 50
                local = 192.168.1.1:3868
                remote = 192.168.2.1:3868
                proto = sctp
            }
            diameter-aaa-server-2 {
                priority = 50
                local = 192.168.1.1:3869
                remote = 192.168.2.2:3868
                proto = tcp
            }
        }
    }
}
```

