

Table of Contents

SWx Authorization Interface Settings	3
Section "charon.plugins.eap-diameter.swx"	3
Section "charon.plugins.eap-diameter.swx.<diameter-hss-server-name-n>"	3

SWx Authorization Interface Settings

Section "charon.plugins.eap-diameter.swx"

Parameter	Description	Value
app_id	Application ID	swx
realm	Serviced realm	epc.mncYYY.mccXXX.3gppnetwork.org
host	Client hostname	epdg.epc.mncYYY.mccXXX.3gppnetwork.org
vendor_id	Vendor ID	[none][3gpp]
<diameter-hss-server-name-1> {}	HSS Server #1 parameters	
<diameter-hss-server-name-2> {}	HSS Server #2 parameters	
<diameter-hss-server-name-n> {}	HSS Server #n parameters	

Example:

```
charon {
    plugins {
        eap-diameter {
            interface = SWx
            SWX {
                app_id = swx
                realm =
epc.mnc002.mcc250.3gppnetwork.org
                host =
epdg.epc.mnc002.mcc250.3gppnetwork.org
                vendor_id = 3gpp
                diameter-hss-server-name-1 {}
                diameter-hss-server-name-2 {}
                diameter-hss-server-name-n {}
            }
        }
    }
}
```

Section "charon.plugins.eap-diameter.swx.<diameter-hss-server-name-n>"

Parameter	Description	Value
priority	Load balancing priority	0-100
local	HSS Server address:port	AAA.BBB.CCC.DDD:XXXX, [1111.2222.3333.4444.5555.6666.7777.8888]:XXXX

Parameter	Description	Value
remote	HSS Client address:port	AAA.BBB.CCC.DDD:XXXX, [1111.2222.3333.4444.5555.6666.7777.8888]:XXXX
proto	Transport protocol	[sctp][tcp]

Example:

```

charon {
    plugins {
        eap-diameter {
            interface = Swx
            swx {
                app_id = swx
                realm =
epc.mnc002.mcc250.3gppnetwork.org
                host =
epdg.epc.mnc002.mcc250.3gppnetwork.org
                vendor_id = 3gpp
                diameter-hss-server-1 {
                    priority = 50
                    local =
192.168.1.1:3868
                    remote =
192.168.2.1:3868
                    proto = sctp
                }
                diameter-hss-server-2 {
                    priority = 30
                    local =
192.168.1.1:3869
                    remote =
192.168.2.2:3868
                    proto = sctp
                }
                diameter-hss-server-3 {
                    priority = 20
                    local =
192.168.1.1:3870
                    remote =
192.168.2.3:3868
                    proto = sctp
                }
            }
        }
    }
}

```