

Содержание

GTP Tunneling Protocol Settings	3
<i>Section "charon.plugins.epdg-pgw.epdg.pgw"</i>	3
<i>Section "charon.plugins.epdg-pgw.epdg.pgw.gtp"</i>	3
<i>Section "charon.plugins.epdg-pgw.epdg.pgw.gtp.gtp-server-name-n"</i>	4
<i>Section "charon.plugins.epdg-pgw.epdg.pgw.gtp.gtp-server-name-n.qos"</i>	5
<i>Section "charon.plugins.epdg-pgw.epdg.pgw.gtp.gtp-server-name-n.gtp-c"</i>	6
<i>Section "charon.plugins.epdg-pgw.epdg.pgw.gtp.gtp-server-name-n.gtp-u"</i>	7

GTP Tunneling Protocol Settings

Section "charon.plugins.epdg-pgw.epdg.pgw"

Parameter	Description	Value
gtp {}	GTP protocol settings	

Example:

```
charon {
    plugins {
        epdg-pgw {
            epdg {
                iface = epdg
                pdn = ipv4
                pgw {
                    gtp {}
                }
            }
        }
    }
}
```

Section "charon.plugins.epdg-pgw.epdg.pgw.gtp"

Parameter	Description	Value
mcc	Operator's MCC	XXX
mnc	Operator's MNC	YYY
realm	Served realm	epc.mncYYY.mccXXX.3gppnetwork.org
gtp-server-name-1 {}	GTP server settings #1	
gtp-server-name-2 {}	GTP server settings #2	
gtp-server-name-n {}	GTP server settings #n	

Example:

```
charon {
    plugins {
        epdg-pgw {
            epdg {
                iface = epdg
                pdn = ipv4
                pgw {
                    gtp {
                        gtp-
server-name-1 {}
                        gtp-
server-name-2 {}
                    }
                }
            }
        }
    }
}
```



```

subnet = 10.1.0.0/16,2001:10::0/48
qos {}
gtp-c {}
gtp-u {}

```

Section "charon.plugins.epdg-pgw.epdg.pgw.gtp.gtp-server-name-n.qos"

Parameter	Description	Value
qci	QCI level	0-9
mbr_ul	Max bitrate uplink	kbits/s
mbr_dl	Max bitrate downlink	kbits/s
gbr_ul	Guaranteed bitrate uplink	kbits/s
gbr_dl	Guaranteed bitrate downlink	kbits/s

Example:

```

charon {
    plugins {
        epdg-pgw {
            epdg {
                iface = epdg
                pdn = ipv4
                pgw {
                    gtp {
                        gtp-
server-name-1 {
    apn = ims
    priority = 50
    devname = tun0
    subnet = 10.1.0.0/16,2001:10::0/48
    qos {
    qci = 5
    mbr_ul = 128
    mbr_dl = 128
    gbr_ul = 128
    gbr_dl = 128
    }
    gtp-c {}
    gtp-u {}
}
}
}
}
}
}
}

```

```
    }
  }
}
```

Section "charon.plugins.epdg-pgw.epdg.pgw.gtp.gtp-server-name-n.gtp-c"

Parameter	Description	Value
local	GTP-C client address	AAA.BBB.CCC.DDD, 1111.2222.3333.4444.5555.6666.7777.8888
remote	GTP-C server address	AAA.BBB.CCC.DDD, 1111.2222.3333.4444.5555.6666.7777.8888

Example:

```
charon {
    plugins {
        epdg-pgw {
            epdg {
                iface = epdg
                pdn = ipv4
                pgw {
                    gtp {
                        gtp-
server-name-1 {
apn = ims
priority = 50
devname = tun0
subnet = 10.1.0.0/16,2001:10::0/48
qos {
qci = 5
mbr_ul = 128
mbr_dl = 128
gbr_ul = 128
gbr_dl = 128
}
gtp-c {
local = 192.168.1.1,2001:1::1
remote = 192.168.2.1,2001:2::1
}
gtp-u {}
}
}
}
}
}
```

Section "charon.plugins.epdg-pgw.epdg.pgw.gtp.gtp-server-name-n.gtp-u"

Parameter	Description	Value
local	GTP-U client address	AAA.BBB.CCC.DDD, 1111.2222.3333.4444.5555.6666.7777.8888
remote	GTP-U server address	AAA.BBB.CCC.DDD, 1111.2222.3333.4444.5555.6666.7777.8888

Example:

```
charon {
    plugins {
        epdg-pgw {
            epdg {
                iface = epdg
                pdn = ipv4
                pgw {
                    gtp {
                        gtp-
server-name-1 {
    apn = ims
    priority = 50
    devname = tun0
    subnet = 10.1.0.0/16,2001:10::0/48
    qos {
    qci = 5
    mbr_ul = 128
    mbr_dl = 128
    gbr_ul = 128
    gbr_dl = 128
    }
    gtp-c {
    local = 192.168.1.1,2001:1::1
    remote = 192.168.2.1,2001:2::1
    }
    gtp-u {
    local = 192.168.1.1,2001:1::1
    remote = 192.168.2.1,2001:2::1
    }
    }
    }
    }
    }
}
```