

Содержание

- Настройки интерфейса авторизации SWm 3
 - Секция "fast-epdg.auth.swm" 3
 - Секция "fast-epdg.auth.swm.<diameter-aaa-server-name-n>" 3

Настройки интерфейса авторизации SWm

Секция "fast-epdg.auth.swm"

Параметр	Описание	Значение
realm	Обслуживаемый реалм	epc.mncYYY.mccXXX.3gppnetwork.org
host	Имя хоста клиента	epdg.epc.mncYYY.mccXXX.3gppnetwork.org
<diameter-aaa-server-name-1> {}	Параметры сервера AAA №1	
<diameter-aaa-server-name-2> {}	Параметры сервера AAA №2	
<diameter-aaa-server-name-n> {}	Параметры сервера AAA №№	

Шаблон:

```
fast-epdg {
  auth {
    interface =
    swm {
      realm =
      host =
      <server-name> {}
    }
  }
}
```

Пример:

```
fast-epdg {
  auth {
    interface = SWm
    swm {
      realm = epc.mnc002.mcc250.3gppnetwork.org
      host = epdg.epc.mnc002.mcc250.3gppnetwork.org
      <server-name> {}
    }
  }
}
```

Секция "fast-epdg.auth.swm.<diameter-aaa-server-name-n>"

Параметр	Описание	Значение
priority	Приоритет балансировки	0-100
local	Адрес:порт клиента	AAA.BBB.CCC.DDD:XXXX, [1111.2222.3333.4444.5555.6666.7777.8888]:XXXX
remote	Адрес:порт сервера AAA	AAA.BBB.CCC.DDD:XXXX, [1111.2222.3333.4444.5555.6666.7777.8888]:XXXX
proto	Транспортный протокол	[sctp][tcp]

Шаблон:

```
fast-epdg {
  auth {
    interface =
    swm {
      realm =
      host =
      diameter-aaa-server-1 {
        priority =
        local =
        remote =
        proto =
      }
      diameter-aaa-server-2 {
        priority =
        local =
        remote =
        proto =
      }
    }
  }
}
```

Пример:

```
fast-epdg {
  auth {
    interface = SWm
    swm {
      realm = epc.mnc002.mcc250.3gppnetwork.org
      host = epdg.epc.mnc002.mcc250.3gppnetwork.org
      diameter-aaa-server-1 {
        priority = 50
        local = 192.168.1.1:3868
        remote = 192.168.2.1:3868
        proto = sctp
      }
      diameter-aaa-server-2 {
        priority = 50
        local = 192.168.1.1:3869
      }
    }
  }
}
```

```
remote = 192.168.2.2:3868  
proto = tcp
```

```
}
```

```
}
```

```
}
```

```
}
```