

# Содержание

<b>SWa Authorization Interface Settings .....</b>	<b>3</b>
<b>Section "fast-epdg.auth.swa" .....</b>	<b>3</b>
<b>Section "fast-epdg.auth.swa.&lt;diameter-aaa-client-name-n&gt;" .....</b>	<b>3</b>



# SWa Authorization Interface Settings

## Section "fast-epdg.auth.swa"

Parameter	Description	Value
app_id	Application ID	swa
realm	Serviced realm	epc.mncYYY.mccXXX.3gppnetwork.org
host	Client hostname	epdg.epc.mncYYY.mccXXX.3gppnetwork.org
<diameter-aaa-client-name-1> {}	AAA Client #1 parameters	
<diameter-aaa-client-name-2> {}	AAA Client #2 parameters	
<diameter-aaa-client-name-n> {}	AAA Client #n parameters	

**Template:**

```
fast-epdg {
    auth {
        interface =
        swa {
            app_id =
            realm =
            host =
            <server-name> {}
        }
    }
}
```

**Example:**

```
fast-epdg {
    auth {
        interface = SWm
        swa {
            app_id = swa
            realm = epc.mnc002.mcc250.3gppnetwork.org
            host = epdg.epc.mnc002.mcc250.3gppnetwork.org
            <server-name> {}
        }
    }
}
```

## Section "fast-epdg.auth.swa.<diameter-aaa-client-name-n>"

Parameter	Description	Value
local	AAA Server address:port	AAA.BBB.CCC.DDD:XXXX, [1111.2222.3333.4444.5555.6666.7777.8888]:XXXX
remote	AAA Client address:port	AAA.BBB.CCC.DDD:XXXX, [1111.2222.3333.4444.5555.6666.7777.8888]:XXXX
proto	Transport protocol	[sctp][tcp]

**Template:**

```
fast-epdg {
    auth {
        interface =
        swa {
            app_id =
            realm =
            host =
            diameter-aaa-client-1 {
                priority =
                local =
                    remote =
                    proto =
            }
            diameter-aaa-client-2 {
                priority =
                local =
                    remote =
                    proto =
            }
        }
    }
}
```

**Template:**

```
fast-epdg {
    auth {
        interface = SWm
        swa {
            app_id = swa
            realm = epc.mnc002.mcc250.3gppnetwork.org
            host = epdg.epc.mnc002.mcc250.3gppnetwork.org
            diameter-aaa-client-1 {
                priority =
                local = 192.168.1.1:3868
                    remote = 192.168.2.1:3868
                    proto = sctp
            }
            diameter-aaa-client-2 {
                priority =
                local = 192.168.1.1:3869
                    remote = 192.168.2.2:3868
            }
        }
    }
}
```

```
        proto = tcp
    }
}
}
```