

Содержание

SWx Authorization Interface Settings	3
<i>Section "fast-epdg.auth.swx"</i>	3
<i>Section "fast-epdg.auth.swx.<diameter-hss-server-name-n>"</i>	3

SWx Authorization Interface Settings

Section "fast-epdg.auth.swx"

Parameter	Description	Value
app_id	Application ID	swx
realm	Serviced realm	epc.mncYYY.mccXXX.3gppnetwork.org
host	Client hostname	epdg.epc.mncYYY.mccXXX.3gppnetwork.org
<diameter-hss-server-name-1> {}	HSS Server #1 parameters	
<diameter-hss-server-name-2> {}	HSS Server #2 parameters	
<diameter-hss-server-name-n> {}	HSS Server #n parameters	

Template:

```
fast-epdg {
  auth {
    interface =
    swx {
      app_id =
      realm =
      host =
      <server-name> {}
    }
  }
}
```

Example:

```
fast-epdg {
  auth {
    interface = SWx
    swx {
      app_id = swx
      realm = epc.mnc002.mcc250.3gppnetwork.org
      host = epdg.epc.mnc002.mcc250.3gppnetwork.org
      <server-name> {}
    }
  }
}
```

Section "fast-epdg.auth.swx.<diameter-hss-server-name-

n>"

Parameter	Description	Value
priority	Load balancing priority	0-100
local	HSS Server address:port	AAA.BBB.CCC.DDD:XXXX, [1111.2222.3333.4444.5555.6666.7777.8888]:XXXX
remote	HSS Client address:port	AAA.BBB.CCC.DDD:XXXX, [1111.2222.3333.4444.5555.6666.7777.8888]:XXXX
proto	Transport protocol	[sctp][tcp]

Template:

```
fast-epdg {
  auth {
    interface =
    swx {
      app_id =
      realm =
      host =
      diameter-hss-server-1 {
        priority =
        local =
        remote =
        proto =
      }
      diameter-hss-server-2 {
        priority =
        local =
        remote =
        proto =
      }
      diameter-hss-server-3 {
        priority =
        local =
        remote =
        proto =
      }
    }
  }
}
```

Example:

```
fast-epdg {
  auth {
    interface = SWx
    swx {
      app_id = swx
      realm = epc.mnc002.mcc250.3gppnetwork.org
    }
  }
}
```

```
host = epdg.epc.mnc002.mcc250.3gppnetwork.org
diameter-hss-server-1 {
    priority = 50
    local = 192.168.1.1:3868
    remote = 192.168.2.1:3868
    proto = sctp
}
diameter-hss-server-2 {
    priority = 30
    local = 192.168.1.1:3869
    remote = 192.168.2.2:3868
    proto = sctp
}
diameter-hss-server-3 {
    priority = 20
    local = 192.168.1.1:3870
    remote = 192.168.2.3:3868
    proto = sctp
}
}
}
}
```